

# **Computational Intelligence**

**Winter Term 2009/10**

Prof. Dr. Günter Rudolph

Lehrstuhl für Algorithm Engineering (LS 11)

Fakultät für Informatik

TU Dortmund

- ▶ **Organization (Lectures / Tutorials)**
- ▶ **Overview CI**
- ▶ **Introduction to ANN**
  - ◆ **McCulloch Pitts Neuron (MCP)**
  - ◆ **Minsky / Papert Perceptron (MPP)**

## Who are you?

either

studying “***Automation and Robotics***” (Master of Science)  
Module “Optimization”

or

studying “***Informatik***”  
- BA-Modul “Einführung in die Computational Intelligence”  
- Hauptdiplom-Wahlvorlesung (SPG 6 & 7)

### Who am I ?

**Günter Rudolph**

Fakultät für Informatik, LS 11

Guenter.Rudolph@tu-dortmund.de  
OH-14, R. 232

← best way to contact me  
← if you want to see me

office hours:  
Tuesday, 10:30–11:30am  
and by appointment

<b>Lectures</b>	Wednesday	10:15-11:45	OH-14, R. E23	
<b>Tutorials</b>	Wednesday	16:15-17:00	OH-14, R. 304	group 1
	Thursday	16:15-17:00	OH-14, R. 304	group 2
<b>Tutor</b>	Nicola Beume, LS11			

### Information

<http://ls11-www.cs.uni-dortmund.de/people/rudolph/teaching/lectures/CI/WS2009-10/lecture.jsp>

**Slides** see web

**Literature** see web

### Knowledge about

- mathematics,
- programming,
- logic

is helpful.


### But what if something is unknown to me?

- covered in the lecture
- pointers to literature

**... and don't hesitate to ask!**

What is CI ?

⇒ umbrella term for computational methods inspired by nature

- artifical neural networks
  - evolutionary algorithms
  - fuzzy systems
  - swarm intelligence
  - artificial immune systems
  - growth processes in trees
  - ...
- 
- The diagram consists of a vertical list of seven items on the left, each preceded by a bullet point. To the right of the list, there are two curly braces. The first brace groups the first four items and is labeled "backbone" to its right. The second brace groups the last three items and is labeled "new developments" to its right.

- term „computational intelligence“ coined by John Bezdek (FL, USA)
- originally intended as a demarcation line  
⇒ establish border between artificial and computational intelligence
- nowadays: blurring border


### our goals:

1. know what CI methods are good for!
2. know when refrain from CI methods!
3. know why they work at all!
4. know how to apply and adjust CI methods to your problem!


### Biological Prototype

- Neuron
  - Information gathering (D)
  - Information processing (C)
  - Information propagation (A / S)


human being:  $10^{12}$  neurons  
electricity in mV range  
speed: 120 m / s



### Abstraction



### Model



McCulloch-Pitts-Neuron 1943:

$$x_i \in \{ 0, 1 \} =: \mathbb{B}$$

$$f: \mathbb{B}^n \rightarrow \mathbb{B}$$

### 1943: Warren McCulloch / Walter Pitts

- description of neurological networks  
→ modell: McCulloch-Pitts-Neuron (MCP)
- basic idea:
  - neuron is either active or inactive
  - skills result from **connecting** neurons
- considered static networks  
(i.e. connections had been constructed and not learnt)



## McCulloch-Pitts-Neuron

n binary input signals  $x_1, \dots, x_n$

threshold  $\theta > 0$

$$f(x_1, \dots, x_n) = \begin{cases} 1 & \text{if } \sum_{i=1}^n x_i \geq \theta \\ 0 & \text{else} \end{cases}$$

⇒ can be realized:




## McCulloch-Pitts-Neuron

n binary input signals  $x_1, \dots, x_n$

threshold  $\theta > 0$

in addition: m binary inhibitory signals  $y_1, \dots, y_m$

$$\tilde{f}(x_1, \dots, x_n; y_1, \dots, y_m) = f(x_1, \dots, x_n) \cdot \prod_{j=1}^m (1 - y_j)$$




- if at least one  $y_j = 1$ , then output = 0
- otherwise:
  - sum of inputs  $\geq$  threshold, then output = 1
  - else output = 0

### Analogons

Neurons	simple MISO processors (with parameters: e.g. threshold)
Synapse	connection between neurons (with parameters: synaptic weight)
Topology	interconnection structure of net
Propagation	working phase of ANN → processes input to output
Training / Learning	adaptation of ANN to certain data


**Assumption:**

inputs also available in inverted form, i.e.  $\exists$  inverted inputs.

**Theorem:**

Every logical function  $F: \mathbb{B}^n \rightarrow \mathbb{B}$  can be simulated with a two-layered McCulloch/Pitts net.

**Example:**  $F(x) = x_1 x_2 \bar{x}_3 \vee \bar{x}_1 \bar{x}_2 \bar{x}_3 \vee x_1 \bar{x}_4$



**Proof:** (by construction)


Every boolean function  $F$  can be transformed in disjunctive normal form

$\Rightarrow$  2 layers (AND - OR)

1. Every clause gets a decoding neuron with  $\theta = n$   
 $\Rightarrow$  output = 1 only if clause satisfied (AND gate)
2. All outputs of decoding neurons  
are inputs of a neuron with  $\theta = 1$  (OR gate)

q.e.d.

### Generalization: inputs with weights





fires 1 if

$$0,2 x_1 + 0,4 x_2 + 0,3 x_3 \geq 0,7 \quad | \cdot 10$$

$$2 x_1 + 4 x_2 + 3 x_3 \geq 7$$



duplicate inputs!



$\Rightarrow$  equivalent!

### Theorem:

Weighted and unweighted MCP-nets are equivalent for weights  $\in \mathbb{Q}^+$ .

### Proof:

„ $\Rightarrow$ “ Let  $\sum_{i=1}^n \frac{a_i}{b_i} x_i \geq \frac{a_0}{b_0}$  with  $a_i, b_i \in \mathbb{N}$

Multiplication with  $\prod_{i=0}^n b_i$  yields inequality with coefficients in  $\mathbb{N}$

Duplicate input  $x_i$ , such that we get  $a_i b_1 b_2 \dots b_{i-1} b_{i+1} \dots b_n$  inputs.

Threshold  $\theta = a_0 b_1 \dots b_n$

„ $\Leftarrow$ “

Set all weights to 1.

q.e.d.

### Conclusion for MCP nets

- + feed-forward: able to compute any Boolean function
- + recursive: able to simulate DFA
- very similar to conventional logical circuits
- difficult to construct
- no good learning algorithm available

## Perceptron (Rosenblatt 1958)

- complex model → reduced by Minsky & Papert to what is „necessary“
- Minsky-Papert perceptron (MPP), 1969


### What can a single MPP do?

$$w_1 x_1 + w_2 x_2 \geq \theta$$

The diagram shows a single MPP with two output paths. The top path is labeled 'J' and leads to an output of 1. The bottom path is labeled 'N' and leads to an output of 0.

isolation of  $x_2$  yields:


$$x_2 \geq \frac{\theta}{w_2} - \frac{w_1}{w_2} x_1$$



### Example:

$$0,9 x_1 + 0,8 x_2 \geq 0,6$$

$$\Leftrightarrow x_2 \geq \frac{3}{4} - \frac{9}{8} x_1$$




separating line

separates  $\mathbb{R}^2$


in 2 classes

$\circ = 0$     $\bullet = 1$


**AND**




**OR**




**NAND**



**NOR**



**XOR**



$x_1$	$x_2$	xor
0	0	0
0	1	1
1	0	1
1	1	0

$$w_1 x_1 + w_2 x_2 \geq \theta$$


$$\begin{aligned} &\Rightarrow 0 < \theta \\ &\Rightarrow w_2 \geq \theta \\ &\Rightarrow w_1 \geq \theta \\ &\Rightarrow w_1 + w_2 < \theta \end{aligned}$$

$$\left. \begin{aligned} &w_1, w_2 \geq \theta > 0 \\ &\Rightarrow w_1 + w_2 \geq 2\theta \end{aligned} \right\}$$

contradiction!


### 1969: Marvin Minsky / Seymour Papert

- book *Perceptrons* → analysis math. properties of perceptrons
- disillusioning result:  
**perceptrons fail to solve a number of trivial problems!**
  - XOR-Problem
  - Parity-Problem
  - Connectivity-Problem
- „conclusion“: All artificial neurons have this kind of weakness!  
⇒ research in this field is a scientific dead end!
- consequence: research funding for ANN cut down extremely (~ 15 years)



how to leave the „dead end“:

1. Multilayer Perceptrons:




⇒ realizes XOR

2. Nonlinear separating functions:

**XOR**

$$g(x_1, x_2) = 2x_1 + 2x_2 - 4x_1x_2 - 1 \quad \text{with} \quad \theta = 0$$



$$\begin{aligned} g(0,0) &= -1 \\ g(0,1) &= +1 \\ g(1,0) &= +1 \\ g(1,1) &= -1 \end{aligned}$$

## How to obtain weights $w_i$ and threshold $\theta$ ?

as yet: by construction

example: NAND-gate

$x_1$	$x_2$	NAND
0	0	1
0	1	1
1	0	1
1	1	0

$$\begin{aligned}\Rightarrow 0 &\geq \theta \\ \Rightarrow w_2 &\geq \theta \\ \Rightarrow w_1 &\geq \theta \\ \Rightarrow w_1 + w_2 &< \theta\end{aligned}$$



requires solution of a system of linear inequalities ( $\in P$ )  
(e.g.:  $w_1 = w_2 = -2, \theta = -3$ )

now: by „learning“ / training


## Perceptron Learning

Assumption: test examples with correct I/O behavior available

### Principle:

- (1) choose initial weights in arbitrary manner
- (2) fed in test pattern
- (3) if output of perceptron wrong, then change weights
- (4) goto (2) until correct output for all test patterns

graphically:



→ translation and rotation of separating lines

## Perceptron Learning


P: set of positive examples  
N: set of negative examples

1. choose  $w_0$  at random,  $t = 0$
2. choose arbitrary  $x \in P \cup N$
3. if  $x \in P$  and  $w_t'x > 0$  then **goto 2**  
if  $x \in N$  and  $w_t'x \leq 0$  then **goto 2**
4. if  $x \in P$  and  $w_t'x \leq 0$  then  
 $w_{t+1} = w_t + x$ ;  $t++$ ; **goto 2**
5. if  $x \in N$  and  $w_t'x > 0$  then  
 $w_{t+1} = w_t - x$ ;  $t++$ ; **goto 2**
6. stop? If I/O correct for all examples!

} I/O correct!  
} let  $w'x \leq 0$ , should be  $> 0$ !  
 $(w+x)'x = w'x + x'x > w'x$   
} let  $w'x > 0$ , should be  $\leq 0$ !  
 $(w-x)'x = w'x - x'x < w'x$

**remark:** algorithm converges, is finite, worst case: exponential runtime

### Example



$$P = \left\{ \begin{pmatrix} 1 \\ 1 \end{pmatrix}, \begin{pmatrix} 1 \\ -1 \end{pmatrix}, \begin{pmatrix} 0 \\ -1 \end{pmatrix} \right\}$$


$$N = \left\{ \begin{pmatrix} -1 \\ -1 \end{pmatrix}, \begin{pmatrix} -1 \\ 1 \end{pmatrix}, \begin{pmatrix} 0 \\ 1 \end{pmatrix} \right\}$$

threshold as a weight:  $w = (\theta, w_1, w_2)'$



$$P = \left\{ \begin{pmatrix} 1 \\ 1 \\ 1 \end{pmatrix}, \begin{pmatrix} 1 \\ 1 \\ -1 \end{pmatrix}, \begin{pmatrix} 1 \\ 0 \\ -1 \end{pmatrix} \right\}$$

$$N = \left\{ \begin{pmatrix} 1 \\ -1 \\ -1 \end{pmatrix}, \begin{pmatrix} 1 \\ -1 \\ 1 \end{pmatrix}, \begin{pmatrix} 1 \\ 0 \\ 1 \end{pmatrix} \right\}$$



suppose initial vector of weights is


$$w^{(0)} = (1, -1, 1)'$$

We know what a single MPP can do.

What can be achieved with many MPPs?

Single MPP  $\Rightarrow$  separates plane in two half planes

Many MPPs in 2 layers  $\Rightarrow$  can identify convex sets




- $\Leftarrow$
1. How?
  2. Convex?

$\forall a, b \in X:$

$$\lambda a + (1-\lambda) b \in X$$

for  $\lambda \in (0,1)$



Single MPP  $\Rightarrow$  separates plane in two half planes

Many MPPs in 2 layers  $\Rightarrow$  can identify convex sets

Many MPPs in 3 layers  $\Rightarrow$  can identify arbitrary sets

Many MPPs in > 3 layers  $\Rightarrow$  not really necessary!

## arbitrary sets:

1. partitioning of nonconvex set in several convex sets
  2. two-layered subnet for each convex set
  3. feed outputs of two-layered subnets in OR gate (third layer)