

# **Computational Intelligence**

**Winter Term 2012/13**

Prof. Dr. Günter Rudolph

Lehrstuhl für Algorithm Engineering (LS 11)

Fakultät für Informatik

TU Dortmund

- ▶ **Organization (Lectures / Tutorials)**
- ▶ **Overview CI**
- ▶ **Introduction to ANN**
  - ◆ **McCulloch Pitts Neuron (MCP)**
  - ◆ **Minsky / Papert Perceptron (MPP)**

### Who are you?

either

studying “*Automation and Robotics*” (Master of Science)  
Module “Optimization”

or

studying “*Informatik*”  
- BA-Modul “Einführung in die Computational Intelligence”  
- Hauptdiplom-Wahlvorlesung (SPG 6 & 7)

### Who am I ?

Günter Rudolph

Fakultät für Informatik, LS 11

Guenter.Rudolph@tu-dortmund.de  
OH-14, R. 232

← best way to contact me  
← if you want to see me

office hours:

Tuesday, 10:30–11:30am  
and by appointment

<b>Lectures</b>	Wednesday	10:15-11:45	OH-14, R. (see web page)
<b>Tutorials</b>	Wednesday or or	08:30-10:00 12:15-13:45 16:15-17:45	MSW16, R. E29, bi-weekly OH14, R. 3.04, bi-weekly MSW16, R. E31, bi-weekly

**Tutor** Dipl.-Inf. Simon Wessing, LS 11

### Information

<http://ls11-www.cs.tu-dortmund.de/people/rudolph/teaching/lectures/CI/WS2012-13/lecture.jsp>

**Slides** see web page  
**Literature** see web page

## Knowledge about

- mathematics,
- programming,
- logic

is helpful.

## But what if something is unknown to me?

- covered in the lecture
- pointers to literature

... and don't hesitate to ask!

### What is CI ?

⇒ umbrella term for computational methods inspired by nature

- artificial neural networks
- evolutionary algorithms
- fuzzy systems
- swarm intelligence
- artificial immune systems
- growth processes in trees
- ...



backbone



new developments

- term „computational intelligence“ coined by John Bezdek (FL, USA)
- originally intended as a demarcation line
  - ⇒ establish border between artificial and computational intelligence
- nowadays: blurring border


### our goals:

1. know what CI methods are good for!
2. know when refrain from CI methods!
3. know why they work at all!
4. know how to apply and adjust CI methods to your problem!


### Biological Prototype

- Neuron
  - Information gathering (D)
  - Information processing (C)
  - Information propagation (A / S)


human being:  $10^{12}$  neurons  
electricity in mV range  
speed: 120 m / s



### Abstraction



### Model



McCulloch-Pitts-Neuron 1943:

$$x_i \in \{ 0, 1 \} =: \mathbb{B}$$

$$f: \mathbb{B}^n \rightarrow \mathbb{B}$$

### 1943: Warren McCulloch / Walter Pitts

- description of neurological networks  
→ modell: McCulloch-Pitts-Neuron (MCP)
- basic idea:
  - neuron is either active or inactive
  - skills result from **connecting** neurons
- considered static networks  
(i.e. connections had been constructed and not learnt)



## McCulloch-Pitts-Neuron

n binary input signals  $x_1, \dots, x_n$

threshold  $\theta > 0$

$$f(x_1, \dots, x_n) = \begin{cases} 1 & \text{if } \sum_{i=1}^n x_i \geq \theta \\ 0 & \text{else} \end{cases}$$

⇒ can be realized:




## McCulloch-Pitts-Neuron

n binary input signals  $x_1, \dots, x_n$

threshold  $\theta > 0$

in addition: m binary inhibitory signals  $y_1, \dots, y_m$


$$\tilde{f}(x_1, \dots, x_n; y_1, \dots, y_m) = f(x_1, \dots, x_n) \cdot \prod_{j=1}^m (1 - y_j)$$



- if at least one  $y_j = 1$ , then output = 0
- otherwise:
  - sum of inputs  $\geq$  threshold, then output = 1
  - else output = 0


**Assumption:**

inputs also available in inverted form, i.e.  $\exists$  inverted inputs.

**Theorem:**

Every logical function  $F: \mathbb{B}^n \rightarrow \mathbb{B}$  can be simulated with a two-layered McCulloch/Pitts net.

**Example:**  $F(x) = x_1 x_2 \bar{x}_3 \vee \bar{x}_1 \bar{x}_2 \bar{x}_3 \vee x_1 \bar{x}_4$



### Proof: (by construction)


Every boolean function  $F$  can be transformed in disjunctive normal form

$\Rightarrow$  2 layers (AND - OR)

1. Every clause gets a decoding neuron with  $\theta = n$   
 $\Rightarrow$  output = 1 only if clause satisfied (AND gate)
2. All outputs of decoding neurons  
are inputs of a neuron with  $\theta = 1$  (OR gate)

q.e.d.

### Generalization: inputs with weights





fires 1 if

$$0,2 x_1 + 0,4 x_2 + 0,3 x_3 \geq 0,7 \quad | \cdot 10$$

$$2 x_1 + 4 x_2 + 3 x_3 \geq 7$$



duplicate inputs!



$\Rightarrow$  equivalent!

**Theorem:**

Weighted and unweighted MCP-nets are equivalent for weights  $\in \mathbb{Q}^+$ .

**Proof:**

„ $\Rightarrow$ “ Let  $\sum_{i=1}^n \frac{a_i}{b_i} x_i \geq \frac{a_0}{b_0}$  with  $a_i, b_i \in \mathbb{N}$

Multiplication with  $\prod_{i=0}^n b_i$  yields inequality with coefficients in  $\mathbb{N}$

Duplicate input  $x_i$ , such that we get  $a_i b_1 b_2 \dots b_{i-1} b_{i+1} \dots b_n$  inputs.

Threshold  $\theta = a_0 b_1 \dots b_n$

„ $\Leftarrow$ “

Set all weights to 1.

q.e.d.

### Conclusion for MCP nets

- + feed-forward: able to compute any Boolean function
- + recursive: able to simulate DFA
- very similar to conventional logical circuits
- difficult to construct
- no good learning algorithm available

### Perceptron (Rosenblatt 1958)

- complex model → reduced by Minsky & Papert to what is „necessary“
- Minsky-Papert perceptron (MPP), 1969 → essential difference:  $x \in [0,1] \subset \mathbb{R}$

### What can a single MPP do?

$$w_1 x_1 + w_2 x_2 \geq \theta$$


isolation of  $x_2$  yields:

$$x_2 \geq \frac{\theta}{w_2} - \frac{w_1}{w_2} x_1$$

### Example:

$$0,9 x_1 + 0,8 x_2 \geq 0,6$$


$$\Leftrightarrow x_2 \geq \frac{3}{4} - \frac{9}{8} x_1$$




separating line  
separates  $\mathbb{R}^2$   
in 2 classes

$\circ = 0$     $\bullet = 1$


**AND**




**OR**




**NAND**



**NOR**



**XOR**



?

$x_1$	$x_2$	xor
0	0	0
0	1	1
1	0	1
1	1	0

$$w_1 x_1 + w_2 x_2 \geq \theta$$

$$\Rightarrow 0 < \theta$$

$$\Rightarrow w_2 \geq \theta$$

$$\Rightarrow w_1 \geq \theta$$

$$\Rightarrow w_1 + w_2 < \theta$$

}


$$w_1, w_2 \geq \theta > 0$$

$$\Rightarrow w_1 + w_2 \geq 2\theta$$

contradiction!


### 1969: Marvin Minsky / Seymour Papert

- book *Perceptrons* → analysis math. properties of perceptrons
- disillusioning result:  
**perceptrons fail to solve a number of trivial problems!**
  - XOR-Problem
  - Parity-Problem
  - Connectivity-Problem
- „conclusion“: All artificial neurons have this kind of weakness!  
⇒ research in this field is a scientific dead end!
- consequence: research funding for ANN cut down extremely (~ 15 years)



how to leave the „dead end“:


1. Multilayer Perceptrons:



2. Nonlinear separating functions:

**XOR**

$$g(x_1, x_2) = 2x_1 + 2x_2 - 4x_1x_2 - 1 \quad \text{with} \quad \theta = 0$$



$$\begin{aligned} g(0,0) &= -1 \\ g(0,1) &= +1 \\ g(1,0) &= +1 \\ g(1,1) &= -1 \end{aligned}$$

## How to obtain weights $w_i$ and threshold $\theta$ ?

as yet: by construction

example: NAND-gate

$x_1$	$x_2$	NAND
0	0	1
0	1	1
1	0	1
1	1	0

$$\begin{aligned}\Rightarrow 0 &\geq \theta \\ \Rightarrow w_2 &\geq \theta \\ \Rightarrow w_1 &\geq \theta \\ \Rightarrow w_1 + w_2 &< \theta\end{aligned}$$



requires solution of a system of linear inequalities ( $\in P$ )  
(e.g.:  $w_1 = w_2 = -2, \theta = -3$ )

now: by „learning“ / training


## Perceptron Learning

Assumption: test examples with correct I/O behavior available

### Principle:


- (1) choose initial weights in arbitrary manner
- (2) feed in test pattern
- (3) if output of perceptron wrong, then change weights
- (4) goto (2) until correct output for all test patterns

graphically:



→ translation and rotation of separating lines

**Example**



$$P = \left\{ \begin{pmatrix} 1 \\ 1 \end{pmatrix}, \begin{pmatrix} -1 \\ -1 \end{pmatrix}, \begin{pmatrix} 1 \\ -1 \end{pmatrix} \right\}$$


$$N = \left\{ \begin{pmatrix} -1 \\ -1 \end{pmatrix}, \begin{pmatrix} -1 \\ 1 \end{pmatrix}, \begin{pmatrix} 0 \\ 1 \end{pmatrix} \right\}$$

threshold as a weight:  $w = (\theta, w_1, w_2)'$



$$P = \left\{ \begin{pmatrix} 1 \\ 1 \\ 1 \end{pmatrix}, \begin{pmatrix} 1 \\ 1 \\ -1 \end{pmatrix}, \begin{pmatrix} 1 \\ 0 \\ -1 \end{pmatrix} \right\}$$

$$N = \left\{ \begin{pmatrix} -1 \\ -1 \\ -1 \end{pmatrix}, \begin{pmatrix} -1 \\ -1 \\ 1 \end{pmatrix}, \begin{pmatrix} 1 \\ 0 \\ 1 \end{pmatrix} \right\}$$



suppose initial vector of weights is

$$w^{(0)} = (1, -1, 1)'$$

## Perceptron Learning

P: set of positive examples  
N: set of negative examples  
threshold  $\theta$  integrated in weights

1. choose  $w_0$  at random,  $t = 0$
2. choose arbitrary  $x \in P \cup N$
3. if  $x \in P$  and  $w_t'x > 0$  then **goto 2**  
if  $x \in N$  and  $w_t'x \leq 0$  then **goto 2**
4. if  $x \in P$  and  $w_t'x \leq 0$  then  
 $w_{t+1} = w_t + x$ ;  $t++$ ; **goto 2**
5. if  $x \in N$  and  $w_t'x > 0$  then  
 $w_{t+1} = w_t - x$ ;  $t++$ ; **goto 2**
6. stop? If I/O correct for all examples!

} I/O correct!  
} let  $w'x \leq 0$ , should be  $> 0$ !  
 $(w+x)'x = w'x + x'x > w'x$   
} let  $w'x > 0$ , should be  $\leq 0$ !  
 $(w-x)'x = w'x - x'x < w'x$


**remark:** algorithm converges, is finite, worst case: exponential runtime

We know what a single MPP can do.

What can be achieved with many MPPs?

Single MPP  $\Rightarrow$  separates plane in two half planes

Many MPPs in 2 layers  $\Rightarrow$  can identify convex sets




- $\Leftarrow$
1. How?
  2. Convex?

$\forall a, b \in X:$

$$\lambda a + (1-\lambda) b \in X$$

for  $\lambda \in (0, 1)$



Single MPP	⇒ separates plane in two half planes
Many MPPs in 2 layers	⇒ can identify convex sets
Many MPPs in 3 layers	⇒ can identify arbitrary sets
Many MPPs in > 3 layers	⇒ not really necessary!

arbitrary sets:

1. partitioning of nonconvex set in several convex sets
2. two-layered subnet for each convex set
3. feed outputs of two-layered subnets in OR gate (third layer)